ACTIVE SPEAKER SYSTEM + MINI MIXER

MX-3



. Dynamic microphone input
. Line input with RCA sockets
. Line input with 1/4 inch socket
. No external power supply required
. Small and versatile dimensions

The Vector-X MX-3 Pre-amplifier module is a micro mixer module designed to work with the PS-5020D powered speaker. The small dimensions of this module allows easy installation. Two stereo line input and one dynamic microphone make the MX-3 suitable for computer labs, classroom, boardrooms and meeting rooms. It is also suitable for multimedia presentations, background music and direct plug and play applications.

SPECIFICATIONS

INPUT SENSITIVITY	Microphone : -60dB Line 1: 775mV Line 2: 775mV
FREQUENCY RESPONSE	30hZ-20kHz
POWER REQUIREMENT	Phantom powered by PS-5020D
DIMENSION (H x W x D)	86mm x 145mm x 65mm (2-gang ABS backbox)
WEIGHT	< 480grams
INPUT CONNECTORS	Microphone : 3-pin XLR Line 1: RCA socket Line 2: 1/4 inch phono jack
OUTPUT CONNECTORS	RJ-45 (Interface to PS-5020D)

DIMENSION

